Combination Masthead/White All-Round Navigation Lights -Plug-in Mount Bases

3-mile (USCG 3nm) Certified

Use on Sail or Power Driven Vessels Under 20m (65.6 ft.) in Length

Material:	Figs. 1123/24: Polymer Top and Zinc Alloy Fig. 1125: Polymer Top and Zinc Alloy Top, Brass Base Fig. 1625: Polymer Top and Zinc Alloy Top, Brass Base	
Finish:	Black and Chrome Plated	
Contacts:	Gold Plated	
Tube:	3/4" Anodized Aluminum	
Screw Size:	#8	
Voltage:	12V LED	12V Incandescent (two bulbs incl.)
Wattage:	2.2 watts (ea. compartment)	10 watts (each compartment)
Amperage:	0.2 amps. (ea. compartment)	80 amps (each compartment)

Features: Two light compartments (Masthead/Anchor)

- Fig. 1123: Horizontal mount
- Fig. 1124: Vertical mount
- Fig. 1125: Deck mount plug-in base with waterproof cover for base that attaches to deck mounted retainer when light is in place.
- Fig. 1625: LED light, deck mount plug-in base with waterproof cover for base that attaches to deck mounted retainer when light is in place. (See wiring note below.)

PROP 65 WARNING (Contains Lead)

Base Mount	Approx. Pole Length	Pole Rake	Base Dimensions	Retail Pkg.	OEM Bulk Pkg.
Horiz. Mt.	15"	45°	2-1/4" x 3/4"	1123DP1CHR	1123001CHR
Horiz. Mt.	28"	45°	2-1/4" x 3/4"	1123DP2CHR	1123002CHR
Vert. Mt.	15"	45°	3/4" x 2-1/4"	1124DP1CHR	1124001CHR
Vert. Mt.	28-3/4"	45°	3/4" x 2-1/4"	1124DP2CHR	1124002CHR
Deck Mt.	35-7/8"	16°	3-3/8" x 2-1/4"	1125DP4CHR	1125004CHR
Deck Mt. LED	34-5/8"	16°	3-3/8" x 2-1/4"	1625DP4CHR	1625004CHR

Fig. 1625 L.E.D.'s have no user serviceable parts

Fig. 1625 Wiring Note: When choosing LED upgrades to replace existing incandescent combination masthead/all-round lights, optional Cat. No. 1680DP012V Converter Module is available to avoid re-wiring the navigation light switch.



Fig. 1680DP012V

Spare Parts Information

Figs. 1123, 1124 & 1125:
12V Bulbs: 0071DP0CLR.
Cap for Base: 0125DP0BLK
Lenses (2 per card): 0278DP0WHT.
Top Cap with Screw: 1158DP0BLK.
Replacement Pole Size 1: 1123DP199A.
Replacement Pole Size 2: 1123DP299A.

Fig. 1123 Base with Socket Assembly: 1123DP099A.
Fig. 1124 Base with Socket Assembly: 1124DP099A.
Fig. 1125/1625 Base with Socket Assembly: 1125DP099A.
Fig. 1125 Replacement Pole Light : 1125DP499A.

Fig. 1123

Fig. 1124

Fig. 1125

Fig. 0278

Fig. 0071DP0CLR